

Model RP4 is a 4PDT Relay Panel with a 24v AC/DC coil for custom control applications. To control relay operation by application of 24v, put jumper between control terminals S2 & S3 and apply 24v to transformer terminals 1 & 2. To control relay operation from a switch or relay contact, continuously apply 24v to transformer terminals 1 & 2 and connect switch type control to control terminals S2 & S3.

